

File: 0x078642a0 [0, 0]

Contents: [Dobrica Pavlinu's random unstructured stuff]

- Dobrica Pavlinu's random unstructured stuff (Full specifications)
- Dobrica Pavlinu's random unstructured stuff (postmarketos)
- Dobrica Pavlinu's random unstructured stuff (modem upgrade)
  - ◆ Dobrica Pavlinu's random unstructured stuff (upgrade modem firmware)

<https://www.pine64.org/pinephone/>

<https://wiki.pine64.org/index.php/PinePhone>

[https://wiki.pine64.org/wiki/PinePhone\\_v1.1\\_-\\_Braveheart](https://wiki.pine64.org/wiki/PinePhone_v1.1_-_Braveheart)

## Full specifications

- 4 x ARM Cortex A53 cores @ 1.152 GHz
- ARM Mali 400 MP2 GPU
- 2GB / 3GB LPDDR3 RAM
- 5.95" LCD 1440 x 720, 18:9 aspect ratio (hardened glass)
- Bootable Micro SD
- 16GB / 32GB eMMC
- HD digital video out
- USB Type C (Power, Data and Video Out)
- Quectel EG25-G with worldwide bands
- Built-in 802.11 b/g/n WiFi with Bluetooth: 4.0
- GNSS: GPS, GPS-A, GLONASS
- Vibration motor
- RGB status LED
- Selfie and Main camera (2/5Mpx respectively)
- Main Camera: Single OV5640, 5MP, 1/4" sensor, LED Flash
- Selfie Camera: Single GC2035, 2MP, f/2.8, 1/5" sensor
- Sensors: accelerator, gyro, proximity, compass, ambient light
- 3 External Switches: volume up, volume down, and power
- Hardware switches: LTE/GNSS, WiFi, Microphone, Speaker, Cameras
- Six pogo pins allowing for custom hardware extensions such as a thermal camera, wireless charging, NFC, an extended battery case, or keyboard case
- Samsung J7 form-factor 3000mAh battery
- Case is matte black finished plastic
- Headphone jack

## postmarketos

[https://wiki.postmarketos.org/wiki/PINE64\\_PinePhone\\_\(pine64-pinephone\)#Installation](https://wiki.postmarketos.org/wiki/PINE64_PinePhone_(pine64-pinephone)#Installation)

```
wget https://images.postmarketos.org/bpo/v21.12/pine64-pinephone/sxmo-de-sway/20220202-0445/20220
```

```
dpavlin@nuc:/tmp$ xz --decompress --stdout 20220202-0445-postmarketOS-v21.12-sxmo-de-sway-1.7.0-p
sudo dd of=/dev/sdc bs=4M status=progress iflag=fullblock oflag=direct conv=fsync
```

# modem upgrade

[https://github.com/the-modem-distro/pinephone\\_modem\\_sdk/](https://github.com/the-modem-distro/pinephone_modem_sdk/)

[https://github.com/the-modem-distro/pinephone\\_modem\\_sdk/blob/kirkstone/docs/AT\\_INTERFACE.md](https://github.com/the-modem-distro/pinephone_modem_sdk/blob/kirkstone/docs/AT_INTERFACE.md)

```
pine64-pinephone:~$ sh -x ./modem-serial.sh
+ sudo picocom --echo --omap ignlf /dev/ttyUSB2
```

```
ati
```

```
Quectel
EG25
Revision: EG25GGBR07A07M2G
```

```
OK
```

```
# battery
AT+CBC
```

```
+CBC: 0,93,4114
```

```
# versions
AT+CGMI
```

```
Quectel
```

```
AT+CGMM
```

```
EG25
```

```
AT+CGMR
```

```
EG25GGBR07A07M2G
```

```
# Get ADSP firmware version
AT+QGMR
```

```
EG25GGBR07A07M2G_01.002.01.002
```

[https://github.com/the-modem-distro/pinephone\\_modem\\_sdk/blob/kirkstone/docs/FLASHING.md#adsp-vers](https://github.com/the-modem-distro/pinephone_modem_sdk/blob/kirkstone/docs/FLASHING.md#adsp-vers)

## upgrade modem firmware

```
pine64-pinephone:/home/user/modem-firmware# sh -x flashall
+ echo 'Sending AT+QFASTBOOT...'
Sending AT+QFASTBOOT...
+ sudo sh -c 'echo -ne "AT+QFASTBOOT\r" > /dev/ttyUSB2'
+ fastboot oem stay
< waiting for any device >
[Mon Jun 12 10:52:53 2023] usb 2-1: USB disconnect, device number 8
[Mon Jun 12 10:52:53 2023] option1 ttyUSB0: GSM modem (1-port) converter now disconnected from tt
[Mon Jun 12 10:52:53 2023] option 2-1:1.0: device disconnected
[Mon Jun 12 10:52:53 2023] option1 ttyUSB1: GSM modem (1-port) converter now disconnected from tt
[Mon Jun 12 10:52:53 2023] option 2-1:1.1: device disconnected
[Mon Jun 12 10:52:53 2023] option1 ttyUSB2: GSM modem (1-port) converter now disconnected from tt
[Mon Jun 12 10:52:53 2023] option 2-1:1.2: device disconnected
[Mon Jun 12 10:52:53 2023] option1 ttyUSB3: GSM modem (1-port) converter now disconnected from tt
[Mon Jun 12 10:52:53 2023] option 2-1:1.3: device disconnected
[Mon Jun 12 10:52:53 2023] qmi_wwan 2-1:1.4 wwan0: unregister 'qmi_wwan' usb-1c1b000.usb-1, WWAN/
```

```
Jun 12 10:52:54 pine64-pinephone authpriv.notice sudo:      root : TTY=pts/0 ; PWD=/home/user/modem
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] port ttyUSB0 released
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] port ttyUSB1 released
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] port ttyUSB2 released
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] port ttyUSB3 released
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] port wwan0 released b
Jun 12 10:52:54 pine64-pinephone daemon.warn [1966]: <warn> Cannot read from istream: connection
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [modem6] port 'cdc-wdm0' no longer c
Jun 12 10:52:54 pine64-pinephone daemon.info NetworkManager[2272]: <info> [1686559974.1549] devi
Jun 12 10:52:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] port cdc-wdm0 release
[Mon Jun 12 10:52:54 2023] usb 2-1: new high-speed USB device number 9 using ehci-platform
FAILED (remote: 'unknown command')
fastboot: error: Command failed
+ fastboot flash about appsboot.mbn
Sending 'about' (279 KB)                                OKAY [ 0.012s]
Writing 'about'                                         OKAY [ 0.145s]
Finished. Total time: 0.168s
+ fastboot reboot
Rebooting                                              OKAY [ 0.017s]
[Mon Jun 12 10:52:55 2023] usb 2-1: USB disconnect, device number 9
Finished. Total time: 0.067s
+ sleep 1
+ fastboot oem stay
< waiting for any device >
[Mon Jun 12 10:52:56 2023] usb 2-1: new high-speed USB device number 10 using ehci-platform
OKAY [ 0.002s]
Finished. Total time: 0.002s
+ sleep 1
+ fastboot flash:raw boot boot-mdm9607.img
< waiting for any device >
Sending 'boot' (4600 KB)                                OKAY [ 0.166s]
Writing 'boot'                                          OKAY [ 1.753s]
Finished. Total time: 1.937s
+ fastboot flash:raw recovery boot-mdm9607.img
Sending 'recovery' (4600 KB)                            OKAY [ 0.162s]
Writing 'recovery'                                     OKAY [ 1.752s]
Finished. Total time: 1.932s
+ fastboot flash system rootfs-mdm9607.ubi
Sending 'system' (27648 KB)                             OKAY [ 0.958s]
Writing 'system'                                       OKAY [ 11.163s]
Finished. Total time: 12.133s
+ fastboot flash recoveryfs recoveryfs.ubi
Sending 'recoveryfs' (13056 KB)                         OKAY [ 0.454s]
Writing 'recoveryfs'                                  OKAY [ 4.686s]
Finished. Total time: 5.153s
+ fastboot reboot
Rebooting                                              OKAY [ 0.004s]
[Mon Jun 12 10:53:20 2023] usb 2-1: USB disconnect, device number 10
Finished. Total time: 0.055s
+ echo 'Done!'
Done!
pine64-pinephone:/home/user/modem-firmware# [Mon Jun 12 10:53:21 2023] usb 2-1: new high-speed US
[Mon Jun 12 10:53:26 2023] usb 2-1: USB disconnect, device number 11
[Mon Jun 12 10:53:42 2023] usb 2-1: new high-speed USB device number 12 using ehci-platform
[Mon Jun 12 10:53:42 2023] option 2-1:1.0: GSM modem (1-port) converter detected
[Mon Jun 12 10:53:42 2023] usb 2-1: GSM modem (1-port) converter now attached to ttyUSB0
[Mon Jun 12 10:53:42 2023] option 2-1:1.1: GSM modem (1-port) converter detected
[Mon Jun 12 10:53:42 2023] usb 2-1: GSM modem (1-port) converter now attached to ttyUSB1
[Mon Jun 12 10:53:42 2023] option 2-1:1.2: GSM modem (1-port) converter detected
[Mon Jun 12 10:53:42 2023] usb 2-1: GSM modem (1-port) converter now attached to ttyUSB2
[Mon Jun 12 10:53:42 2023] option 2-1:1.3: GSM modem (1-port) converter detected
[Mon Jun 12 10:53:42 2023] usb 2-1: GSM modem (1-port) converter now attached to ttyUSB3
[Mon Jun 12 10:53:42 2023] qmi_wwan 2-1:1.4: cdc-wdm0: USB WDM device
[Mon Jun 12 10:53:42 2023] qmi_wwan 2-1:1.4 wwan0: register 'qmi_wwan' at usb-1c1b000.usb-1, WWAN
Jun 12 10:53:43 pine64-pinephone user.notice postmarketOS:modem-setup: Modem already configured
Jun 12 10:53:54 pine64-pinephone daemon.info [1966]: <info> [device /sys/devices/platform/soc/1c
```

```
Jun 12 10:53:54 pine64-pinephone daemon.warn [1966]: <warn> [plugin/quectel] could not grab port
Jun 12 10:53:54 pine64-pinephone daemon.info [1966]: <info> [base-manager] modem for device '/sy
Jun 12 10:53:55 pine64-pinephone daemon.warn [1966]: <warn> [modem7] couldn't query SIM slots: Q
Jun 12 10:53:56 pine64-pinephone daemon.warn [1966]: <warn> [modem7/sim5] couldn't load list of
Jun 12 10:53:56 pine64-pinephone daemon.warn [1966]: <warn> [modem7] couldn't load list of own n
Jun 12 10:53:56 pine64-pinephone daemon.info [1966]: <info> [modem7] state changed (unknown -> d
Jun 12 10:53:56 pine64-pinephone daemon.info NetworkManager[2272]: <info> [1686560036.9081] mana
Jun 12 10:53:56 pine64-pinephone daemon.info NetworkManager[2272]: <info> [1686560036.9131] devi
Jun 12 10:53:56 pine64-pinephone daemon.info NetworkManager[2272]: <info> [1686560036.9154] devi
Jun 12 10:53:56 pine64-pinephone daemon.info NetworkManager[2272]: <info> [1686560036.9182] devi
Jun 12 10:53:56 pine64-pinephone daemon.info [1966]: <info> [modem7] state changed (disabled ->
Jun 12 10:53:57 pine64-pinephone daemon.info [1966]: <info> [modem7] power state updated: on
Jun 12 10:53:57 pine64-pinephone daemon.info [1966]: <info> [modem7] state changed (enabling ->
Jun 12 10:53:57 pine64-pinephone daemon.info [1966]: <info> [modem7] 3GPP registration state cha
Jun 12 10:53:57 pine64-pinephone daemon.info [1966]: <info> [modem7] 3GPP registration state cha
Jun 12 10:53:57 pine64-pinephone daemon.info [1966]: <info> [modem7] state changed (enabled -> r
Jun 12 10:54:06 pine64-pinephone daemon.warn [1966]: <warn> [modem7] couldn't load network timez
```

```
pine64-pinephone:/home/user/modem-firmware#
```

```
pine64-pinephone:/home/user/modem-firmware# fwupdmgr get-devices
```

```
Jun 12 10:54:17 pine64-pinephone authpriv.notice polkitd[2031]: Registered Authentication Agent f
WARNING: UEFI capsule updates not available or enabled in firmware setup
```

```
See https://github.com/fwupd/fwupd/wiki/PluginFlag:capsules-unsupported for more information.
```

```
WARNING: This package has not been validated, it may not work properly.
```

```
pine64 Pine64 PinePhone Braveheart (1.1)
```

```
â
```

```
â â Unknown Device:
```

```
â Device ID: 0e0c93c8b4bb222157feedbde8f863e23bd1a8f7
```

```
â Current version: 0x1400000000000000
```

```
â Vendor: EMMC:0x0000e1
```

```
â GUID: ba81658c-572e-5097-a08f-f9f023bb4224 â EMMC\MAN_00E1&OEM_0116
```

```
â Device Flags: â ¢ Internal device
```

```
â â ¢ Updatable
```

```
â
```

```
â â QUECTEL Mobile Broadband Module:
```

```
Device ID: 976c4a39e87f61e6940ea6a8d39c583cfa99615f
```

```
Summary: Quectel EG25-G modem
```

```
Current version: EG25GGBR07A07M2G_01.002.01.002
```

```
Vendor: Qualcomm (USB:0x2C7C, USB:0x18D1)
```

```
GUIDs: db379a33-254f-5140-b37e-d36ae7e5c039
```

```
d18f31f1-a3fa-55a2-b4ed-decfbc1e004d â USB\VID_2C7C&PID_0125&REV_0318
```

```
1a2996cb-f86e-5583-a464-e1b96e1c6ae9 â USB\VID_2C7C&PID_0125&REV_0318
```

```
587bf468-6859-5522-93a7-6cce552a0aa3 â USB\VID_2C7C&PID_0125
```

```
22ae45db-f68e-5c55-9c02-4557dca238ec â USB\VID_2C7C
```

```
Device Flags: â ¢ Updatable
```

```
â ¢ System requires external power source
```

```
â ¢ Supported on remote server
```

```
â ¢ Device supports switching to a different branch of firmware
```

```
â ¢ Unsigned Payload
```