

<https://tasmota.github.io/docs/devices/Nedis-WIFIP310FWT/>

https://templates.blakadder.com/nedis_WIFIP310FWT.html

Description: 3 port AC outlets (European Schucko Type F) + 4 USB power outlets

Power input: 16 A - 230 VAC

Max. Power: 3680 W

Power output: USB: 5 VDC /2.4 A each

mapping

GPIO #	Component	
GPIO00	None	[0,1]
GPIO01	Led1i	[1,1]
GPIO02	None	[2,1]
GPIO03	Button1	[3,1]
GPIO04	Relay2	[4,1]
GPIO05	Relay1	[5,1]
GPIO09	None	[6,1]
GPIO10	None	[7,1]
GPIO12	None	[8,1]
GPIO13	Relay3	[9,1]
GPIO14	Relay4	[10,1]
GPIO15	None	[11,1]
GPIO16	None	[12,1]
FLAG	Analog	[13,1]

Template:

```
{"NAME": "Nedis WIFIP310", "GPIO": [0, 56, 0, 17, 22, 21, 0, 0, 0, 23, 24, 0, 0], "FLAG": 1, "BASE": 18}
```

new template for version 9

```
IO": [0, 320, 0, 32, 225, 224, 0, 0, 0, 226, 227, 0, 0, 4704], "FLAG": 0, "BASE": 18}
```